


# LDC0800 QUICK PROGRAMMING GUIDE

## ADDING A TRANSMITTER OR KEYPAD CODE

-  UP +  
 DOWN - PRESS & RELEASE  
LEARN BUTTON



 LEARN

 RED LED WILL LIGHT FOR 15 SECONDS - READY TO LEARN


 PUSH TRANSMITTER BUTTON OR ENTER KEYPAD CODE

 1 FLASH = TRANSMITTER BUTTON OR KEYPAD CODE LEARNED


## ERASING A TRANSMITTER OR KEYPAD CODE

-  UP +  
 DOWN - PRESS & RELEASE  
LEARN BUTTON

 LEARN

 RED LED WILL LIGHT FOR 15 SECONDS - READY TO ERASE


 PUSH TRANSMITTER BUTTON OR ENTER KEYPAD CODE

 4 FLASHES = TRANSMITTER BUTTON OR KEYPAD CODE ERASED

## ERASING ALL TRANSMITTERS & KEYPADS



- 10  
SEC.  UP +  
 DOWN - PRESS LEARN BUTTON  
FOR 10 SECONDS

 LEARN

 3 FLASHES = ALL TRANSMITTERS & KEYPADS ERASED



## SETTING THE OPEN LIMIT

NOTE: LIMITS ARE PRESET FOR 7-FOOT DOORS

-  UP +  
 DOWN - PRESS LEARN & UP  
FOR 3 SECONDS

 LEARN


 2 GREEN FLASHES = SET UP LIMIT

-  UP +  
 DOWN - PRESS UP (+) OR DOWN (-)  
TO JOG THE DOOR TO THE  
CORRECT POSITION



 LEARN

 UP +  
 DOWN - PRESS LEARN TO STORE LIMIT

 LEARN



 2 GREEN FLASHES = OPEN LIMIT STORED

## SETTING THE CLOSE LIMIT


-  UP +  
 DOWN - PRESS LEARN & DOWN  
FOR 3 SECONDS

 LEARN

 2 RED FLASHES = SET DOWN LIMIT

-  UP +  
 DOWN - PRESS UP (+) OR DOWN (-)  
TO JOG THE DOOR TO THE  
CORRECT POSITION

 LEARN

 UP +  
 DOWN - PRESS LEARN TO STORE LIMIT

 LEARN

 2 RED FLASHES = CLOSE LIMIT STORED

## SETTING THE DOOR FORCE



RUN THE OPERATOR FOUR COMPLETE UP & DOWN CYCLES



THE OPERATOR AUTOMATICALLY SETS THE CORRECT DOOR FORCE

FOR OPTIONAL OPEN AND CLOSE FORCE MODIFICATIONS, SEE INSTRUCTIONS

**Linear**<sup>®</sup>  
*Building On Innovation.*

USA & Canada (800) 421-1587 & (800) 392-0123  
(760) 438-7000 - Toll Free FAX (800) 468-1340

[www.linearcorp.com](http://www.linearcorp.com)



USA & Canada (800) 421-1587 & (800) 392-0123  
(760) 438-7000 – Toll Free FAX (800) 468-1340  
[www.linearcorp.com](http://www.linearcorp.com)